

DUNCAN humbuckers:
Output ("hot") is BLACK.
Coil tap wires white/red.
Ground wire is GREEN,
also BARE (shield) wire.

Dimarzio humbuckers:
Output ("hot") is RED.
Coil tap wires white/black.
Ground wire is GREEN,
also BARE (shield) wire.

SUSTAINIAC® STEALTH PRO INSTALLATION

3-PICKUP GUITAR

10-15

3PU #3

NOTES:

1. **Orient board to place 8-pin connector close to pickup selector. Trim white/orange wires (8-pin) short.**
2. Make sure that all pot bodies are connected to ground and also to output jack shield terminal.
3. Make sure that battery (-) wire and black wire of 10-pin connector go to same ground connection.
4. Bridge, middle pickup ground and shield wires not shown. These connect to ground (pot body)
5. Route violet/gray pair of 10-pin away from pickup signal wires.

